# Yuasa Technical Data Sheet

## Yuasa NP10-6 Industrial VRLA Battery

<b>Specifications</b> Nominal voltage (V) 10-hr rate Capacity to 1.8V/Cell at 20°C (Ah)	6 9.2
<b>Dimensions</b> Length (mm) Width (mm) Height over terminals (mm) Mass (kg)	151 (±1) 50 (±1) 97.5 (±2) 1.93
<b>Terminal Type</b> FASTON - Quickfit / release (JST where stated)	4.75
<b>Operating Temperature Range</b> Storage (in fully charged condition) Charge Discharge	-20°C to +60°C -15°C to +50°C -20°C to +60°C
<b>Storage</b> Capacity loss per month at 20°C (% approx.)	3
<b>Case Material</b> Standard FR version available	ABS (UL94:HB) UL94:V0
<b>Charge Voltage</b> Float charge voltage at 20°C (V)/Block Float charge voltage at 20°C (V)/Cell Float Chg voltage tmp correction factor from std 20°C (mV)	6.825 (±1%) 2.275 (±1%) -3
Cyclic (or Boost) charge Voltage at 20°C (V)/Block Cyclic (or Boost) charge Voltage at 20°C (V)/Cell Cyclic Chg voltage tmp correction factor from std 20°C (mV)	7.26 (±3%) 2.42 (±3%) -4
<b>Charge Current</b> Float charge current limit (A) Cyclic (or Boost) charge current limit (A)	No limit 2.5
<b>Maximum Discharge Current</b> 1 second (A) 1 minute (A)	300 48
<b>Impedance</b> Measured at 1 kHz (mΩ)	8
<b>Design Life &amp; Approvals</b> EUROBAT Classification: Standard Commercial Yuasa design life at 20°C (yrs)	3 to 5 years up to 5





## Layout



### **3rd Party Certifications** ISO9001 - Quality Management Systems

# Safety

#### Installation

Can be installed and operated in any orientation except permanently inverted.

# Handles

Batteries must not be suspended by their handles (where fitted).

# Vent valves

Each cell is fitted with a low pressure release valve to allow gasses to escape and then reseal.

## Gas release

VRLA batteries release hydrogen gas which can form explosive mixtures in the air. Do not place inside a sealed container.

#### Recycling

YUASA's VRLA batteries must be recycled at the end of life in accordance with local and national laws and regulations.



Data Sheet generated on 29/04/2024 - E&OE



Adress:Ferhatpaşa Mah. 43. Sk. No: 52-54, 34888 Ataşehir / İstanbul, TürkiyePhone:+90 216 466 95 50WhatsApp: +90 532 318 02 06Web:upselektronik.com / riello-ups.com.trMail: info@riello-ups.com.tr

