# Yuasa Technical Data Sheet

# Yuasa NP18-12B Industrial VRLA Battery

**Specifications** 

Nominal voltage (V) 12 10-hr rate Capacity to 1.8V/Cell at 20°C (Ah) 16 20-hr rate Capacity to 1.75V/Cell at 20°C (Ah) 17.2

**Dimensions** 

 Length (mm)
  $180 (\pm 1)$  

 Width (mm)
  $76 (\pm 1)$  

 Height (mm)
  $167 (\pm 2)$  

 Mass (kg)
 6.2 

**Terminal Type** 

Threaded terminal - (M=Male or F=Female) M5 Lug

**Operating Temperature Range** 

Storage (in fully charged condition)  $-20^{\circ}\text{C}$  to  $+60^{\circ}\text{C}$  Charge  $-15^{\circ}\text{C}$  to  $+50^{\circ}\text{C}$  Discharge  $-20^{\circ}\text{C}$  to  $+60^{\circ}\text{C}$ 

**Storage** 

Capacity loss per month at 20°C (% approx.)

**Case Material** 

Standard ABS (UL94:HB)
FR version available UL94:V0

**Charge Voltage** 

Float charge voltage at 20°C (V)/Block 13.65 ( $\pm$ 1%) Float charge voltage at 20°C (V)/Cell 2.275 ( $\pm$ 1%)

Float Chg voltage tmp correction factor from std -3

20°C (mV)

Cyclic (or Boost) charge Voltage at  $20^{\circ}$ C (V)/Block 14.5 ( $\pm 3\%$ ) Cyclic (or Boost) charge Voltage at  $20^{\circ}$ C (V)/Cell 2.42 ( $\pm 3\%$ ) Cyclic Chg voltage tmp correction factor from std -4

20°C (mV)

**Charge Current** 

Float charge current limit (A) No limit Cyclic (or Boost) charge current limit (A) 4.5

**Maximum Discharge Current** 

1 second (A) 500 1 minute (A) 150

**Impedance** 

Measured at 1 kHz (m $\Omega$ ) 15


**Design Life & Approvals** 

EUROBAT Classification: Standard Commercial 3 to 5 years Yuasa design life at 20°C (yrs) up to 5





Layout



# **3rd Party Certifications**

ISO9001 - Quality Management Systems

# Safety

# Installation

Can be installed and operated in any orientation except permanently inverted.

#### Handles

Batteries must not be suspended by their handles (where fitted).

#### **Vent valves**

Each cell is fitted with a low pressure release valve to allow gasses to escape and then reseal.

#### Gas release

VRLA batteries release hydrogen gas which can form explosive mixtures in the air. Do not place inside a sealed container.


### Recycling

YUASA's VRLA batteries must be recycled at the end of life in accordance with local and national laws and regulations.











 Adress:
 Ferhatpaşa Mah. 43. Sk. No: 52-54, 34888 Ataşehir / İstanbul, Türkiye

 Phone:
 +90 216 466 95 50
 WhatsApp: +90 532 318 02 06

 Web:
 upselektronik.com / riello-ups.com.tr
 Mail: info@riello-ups.com.tr

32 318 02 06 ps.com.tr